

QuickQ 30



CHAMQUICKQ30

Features

- 4 Universe Console, ideal for conventional, LED and moving light control
- Intuitive Smart phone style Interface
- Inbuilt Wi-Fi for connection of iOS and Android remotes
- Large 9.7" Multi-touch display
- Multi-Touch gesture support for fixture control
- RDM Support for RDM Autopatch
- Free QuickQ designer offline software
- 10 Multi-function playbacks
- Multi Function fixture faders with Fixture, Group or Cue mode
- Supports connection to Free MagicVis Visualiser

Hardware Specifications

- Inbuilt Wi-Fi
- Encoders: 6, 4 attribute plus 2 dedicated Hue & Saturation
- DMX Ports: 3
- Network ports: 1, with Artnet & sACN support
- Audio: In & Out
- MIDI: In & Out
- External Monitor: 1 HDMI
- USB Ports: 2
- Multi-Function Fixture faders: 40
- Playbacks: 10

Software Specifications

- Universes: 4
- Channels: 2048
- Number of fixtures: limited by channels supported
- RDM Autopatch for fast show patching
- Fixture library of over 25,000 fixture files
- Built in FX generator
- Colour picker and Gel inbuilt Gel library
- Offline designer software available for Windows and Mac